

## Model Definition

Inverter model	Motor adapter		Rated input A	Rated output A
	kW	HP		
1PH single phase input: AC 220V, 50/60Hz				
HV390-R40G1-2	0.4	0.5	5.9	2.5
HV390-R75G1-2	0.75	1	8.3	4
HV390-1R5G1-2	1.5	2	14.1	7
3PH 3-phase input: AC 220V, 50/60Hz				
HV390-R40G2	0.4	0.5	4.1	2.5
HV390-R75G2	0.75	1	5.3	4
HV390-1R5G2	1.5	2	8.0	7
3PH 3-phase input: AC 380V, 50/60Hz				
HV390-R40G3	0.4	0.5	-	-
HV390-R75G3	0.75	1	4.3	2.5
HV390-1R5G3	1.5	2	5.2	3.7
HV390-2R2G3	2.2	3	6.0	5
HV390-004G3	4.0	5	10.5	8.5
HV390-5R5G3	5.5	7.5	15.5	13
3PH 3-phase input: AC 460V, 50/60Hz				
HV390-R40G4	0.4	0.5	-	-
HV390-R75G4	0.75	1	4.1	2.5
HV390-1R5G4	1.5	2	4.9	3.7
HV590-2R2G4	2.2	3	5.7	5
HV390-004G4	4.0	5	9.4	8
HV390-5R5G4	5.5	7.5	12.5	11