

Model Definition

| Model | Power supply capacity (KVA) | Input current (A) | Output current (A) | Adaptive motor (KW) | (HP) |
|---|-----------------------------|-------------------|--------------------|---------------------|------|
| Three - phase power supply: 380V 50 / 60 Hz | | | | | |
| HV610-R75G3 | 1.5 | 3.4 | 2.1 | 0.75 | 1 |
| HV610-1R5G3 | 3.0 | 5.0 | 3.8 | 1.5 | 2 |
| HV610-2R2G3 | 4.0 | 5.8 | 5.1 | 2.2 | 3 |
| HV610-004G3 | 5.9 | 10.5 | 9.0 | 4.0 | 5 |
| HV610-5R5G3 | 8.9 | 14.6 | 13.0 | 5.5 | 7.5 |
| HV610-7R5G3 | 11 | 20.5 | 17.0 | 7.5 | 10 |
| HV610-011G3 | 17 | 26.0 | 25.0 | 11 | 15 |
| HV610-015G3 | 21 | 35.0 | 32.0 | 15 | 20 |
| HV610-018G3 | 45 | 42 | 37 | 18.5 | 25 |
| HV610-022G3 | 54 | 50 | 45 | 22 | 30 |
| HV610-030G3 | 60 | 68 | 60 | 30 | 40 |
| HV610-037G3 | 63 | 83 | 75 | 37 | 50 |
| HV610-045G3 | 81 | 102 | 91 | 45 | 60 |
| HV610-055G3 | 97 | 124 | 112 | 55 | 75 |
| HV610-075G3 | 127 | 169 | 150 | 75 | 100 |
| HV610-093G3 | 150 | 203 | 176 | 90 | 125 |
| HV610-110G3 | 179 | 248 | 210 | 110 | 150 |
| HV610-132G3 | 192 | 256 | 253 | 132 | 175 |
| HV610-160G3 | 231 | 307 | 304 | 160 | 220 |
| HV610-185G3 | 242 | 350 | 340 | 185 | 245 |
| HV610-200G3 | 250 | 385 | 377 | 200 | 270 |
| HV610-220G3 | 280 | 430 | 426 | 220 | 300 |
| HV610-250G3 | 355 | 468 | 465 | 250 | 340 |
| HV610-280G3 | 396 | 525 | 520 | 280 | 380 |
| HV610-315G3 | 445 | 590 | 585 | 315 | 430 |
| HV610-355G3 | 500 | 665 | 650 | 355 | 420 |
| HV610-400G3 | 565 | 785 | 725 | 400 | 530 |
| HV610-450G3 | 630 | 883 | 820 | 450 | 600 |
| HV610-500G3 | 720 | 954 | 920 | 500 | 670 |
| HV610-560G3 | 780 | 1085 | 1030 | 560 | 750 |